

Single Output Module

CHQ-SOM



Features

- ▶ Includes a single monitored output
- ▶ Small design for simple provision of a monitored output onto an ESP loop
- ▶ Flying leads for easy installation
- ▶ Addressed with TCH-B100 Hand Held Programmer
- ▶ Approved by LPCB

Description

The CHQ-SOM has been designed to allow a single relay output to be connected to the ESP loop. The unit incorporates a volt-free relay contact that can be configured as either N/O or N/C, the relay contact is rated to 30 V dc (max), 1 A (resistive load). The CHQ-SOM features three colour-coded flying leads, the unit also features a wiring terminal block for loop connection.

NOTE: The state of the relay contacts will be indeterminate until the unit is powered.

To maintain LPCB approval the device **must** be mounted in an SMB-1 enclosure (or an equivalent enclosure made from polycarbonate or a similar material which is impact resistant as per EN54-18:2005 Clause 5.9) in conjunction with the SMB-ADAPTOR plate, using two M3 screws or two M3 nuts and bolts.

NOTE: If the PCB is removed from the protective outer casing the EN54 approval is voided.

Specification

Ordering code	CHQ-SOM*
Operating voltage	17 – 41 V dc
Quiescent Current / Alarm Current	150 μ A (at 41 V) max
Output Ratings	Max voltage
	30 V dc
Output Ratings	Max current
	1 A (resistive load)
Operating temperature range	-10 °C to + 50 °C
Storage temperature range	-20 °C to + 60 °C
Maximum humidity	95% RH - Non condensing (at 40 °C)
Colour / Case material	Ivory / ACS
Weight (g) / Length / Width / Depth (mm)	25 / 65 / 42 / 15
Approval	LPCB

*Fire alarm control panel compatibility is required for this product

Hochiki Europe (UK) Ltd. reserves the right to alter the specification of its products from time to time without notice. Although every effort has been made to ensure the accuracy of the information contained in this document it is not warranted or represented by Hochiki Europe (UK) Ltd. to be a complete and up-to-date description.