

ACD-EN

Addressable Multi-Sensor with CO Detection

Features

- ▶ Low profile
- ▶ Heat, optical and CO sensing elements
- ▶ CO Alarm (COHb) facility
- ▶ 10 year CO sensor life*¹
- ▶ Programmable fire threshold level
- ▶ RI & LED controllable separately if required*²
- ▶ 2 colour LED (Polling: green, fire: RED)
- ▶ 24 EN approved modes of operation.



Description

An addressable loop-powered multi-sensor, with smoke, heat and CO sensing elements. The unit offers 24 different modes of operation*² and seamlessly matches the other sensors in the ESP Range.

The CO sensing element can be used to detect smoke as well as life-threatening CO levels (acting as a CO alarm).

Note: Control Panel compatibility required

Specification

Ordering Code	ACD-EN - Ivory ACD-EN(WHT) - White	
Operating Voltage	17 – 41 VDC	
Loop Pulse Voltage	7 – 9 VDC	
Current Consumption	Quiescent	410 μ A (typ)* ³
	Loop current (when polled)	22 mA \pm 20%* ³
	Remote Indicator	8.0 mA \pm 20%* ³
	LED current	9.1 mA* ³
	Surge current	40 mA (for 50 ms)
Operating Temperature Range* ⁴	- 10 °C to + 50 °C	
Relative Humidity	<95% RH (at 40 °C) <80% RH (at 50 °C)	
Storage Temperature Range	- 20 °C to + 50 °C	
Colour / Case Material	Ivory or white / polycarbonate (outer cover) / PC/PS-GF (terminal plate)	
Weight without Base (g)	105	
Diameter (mm) / Height (mm)	\varnothing 100 / 45 (without base)	
Compatible Bases	YBN-R/3, YBN-R/3(SCI), YBO-BS, YBO-BSB2	
Approvals	EN 54-5:2017 + A1:2018, EN 54-7:2018, EN 54-26:2015, EN 54-29:2015, EN 54-30:2015, EN 54-31:2015, CEA 4021:2003	

Note: This sensor does not support sleep mode.

*¹ Dependent on operational usage.

*² Panel compatibility dependant.

*³ Currents are cumulative.

*⁴ Operating temperature complies with standard sensitivity.



For further information visit our website. Hochiki reserves the right to alter the specification of its products from time to time without notice. Although every effort has been made to ensure the accuracy of the information contained in this document it is not warranted or represented by Hochiki to be a complete and up-to-date description. Check online for current version.